

Inhaltsverzeichnis

- Compiling QCANObserver on Ubuntu 12.04** 3
- Prerequisites*** 3
- Download & compile the QCANObserver Code*** 3
- Compiling the socket driver*** 3
- Run QCANObserver*** 4

Compiling QCANObserver on Ubuntu 12.04

Prerequisites

Install the QT4 development packages, where qtcreator itself is not needed, but it helps to install the whole environment

```
sudo apt-get install libqwt5-qt4-dev libqwt5-qt4 qtcreator
```

Download & compile the QCANObserver Code

```
svn co https://qcanobserver.svn.sourceforge.net/svnroot/qcanobserver
qcanobserver
cd qcanobserver
qmake
```

After running qmake as above, make a few tweaks in the generated makefile:

In the parameter „INCPATH =“ change

```
-I/usr/include/qwt5
```

to

```
-I/usr/include/qwt-qt4
```

and in „LIBS =“ change

```
-lqwt
```

to

```
-lqwt-qt4
```

Then run

```
make
```

Compiling the socket driver

```
cd DeviceLib/linux/SocketCAN
qmake
make
cp libSocketCAN.so ../../../../lib/
```

Run QCANObserver

change into the QCANObserver directory and just start the program

```
./QCan0bserver
```

From:

<http://koehlers.de/wiki/> - **Steffen Köhlers Online- Bastelbuch**

Permanent link:

<http://koehlers.de/wiki/doku.php?id=pc:qcanobserver>

Last update: **2013/04/06 08:21**

